6ES7136-6AA00-0CA1

**Data sheet** 



SIMATIC DP, electronic module ET 200SP, F-AI 4xI0(4)..20 mA HF fail-safe analog inputs up to PL e (ISO 13849) up to SIL 3 (IEC 61508)

General information		
Product type designation	F-AI 4xI 0(4)20mA 2-/4-wire HF	
Firmware version		
FW update possible	Yes	
usable BaseUnits	BU type A0, A1	
Color code for module-specific color identification plate	CC00	
Product function		
• I&M data	Yes; I&M0 to I&M3	
Engineering with		
STEP 7 TIA Portal configurable/integrated from version	V15 with HSP 203	
CiR - Configuration in RUN		
Reparameterization possible in RUN	No	
Calibration possible in RUN	No	
Supply voltage		
Rated value (DC)	24 V	
permissible range, lower limit (DC)	19.2 V	
permissible range, upper limit (DC)	28.8 V	
Reverse polarity protection	Yes	
power supply according to NEC Class 2 required	No	
Input current		
Current consumption (rated value)	0.38 A	
Current consumption, max.	0.4 A	
Encoder supply		
24 V encoder supply		
• 24 V	Yes; min. L+ (-1.5 V)	
Short-circuit protection	Yes	
<ul> <li>Output current, max.</li> </ul>	300 mA; total current of all encoders/channels	
Power		
Power available from the backplane bus	70 mW	
Power loss		
Power loss, typ.	2 W	
Address area		
Address space per module		
• Inputs	14 byte; S7-300/400F CPU, 13 byte	
Outputs	5 byte; S7-300/400F CPU, 4 byte	
Hardware configuration		
Automatic encoding	Yes	
<ul> <li>Electronic coding element type F</li> </ul>	Yes	
Analog inputs		
Number of analog inputs	4	

For current measurement	4	
permissible input current for current input (destruction limit), max.	35 mA	
Input ranges (rated values), currents		
• 0 to 20 mA	Yes	
— Input resistance (0 to 20 mA)	125.0	
• 4 mA to 20 mA	Yes	
— Input resistance (4 mA to 20 mA)	125 Ω	
Cable length	120 12	
shielded, max.	1 000 m	
Analog value generation for the inputs	1 000 III	
Measurement principle	Sigma Delta	
Integration and conversion time/resolution per channel	Signia Della	
Resolution with overrange (bit including sign), max.	16 bit	
Integration time, parameterizable	Yes	
Integration time, parameterizable     Integration time (ms)	20 / 16,667	
	50 / 60 Hz	
<ul> <li>Interference voltage suppression for interference frequency f1 in Hz</li> </ul>	30 / 60 HZ	
Smoothing of measured values		
Number of smoothing levels	7	
parameterizable	Yes	
Step: None	Yes; 1x conversion cycle time	
• Step: low	Yes; 2x / 4x conversion cycle time	
Step: Medium	Yes; 8x / 16x conversion cycle time	
• Step: High	Yes; 32x / 64x conversion cycle time	
Encoder		
Connection of signal encoders		
for current measurement as 2-wire transducer	Yes	
Burden of 2-wire transmitter, max.	650 Ω	
for current measurement as 4-wire transducer	Yes	
Errors/accuracies		
Linearity error (relative to input range), (+/-)	0.1 %	
Temperature error (relative to input range), (+/-)	0.023 %/K	
Tomporatare error (rolative to input range), (*/ )		
Repeat accuracy in steady state at 25 °C (relative to input range). (+/-)	0.1 %	
range), (+/-)	0.1 %	
range), (+/-) Operational error limit in overall temperature range		
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)	2 %	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)	2 %	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)	2 % 0.1 %	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)	2 % 0.1 %	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference work and interference (peak value of interference <	2 %  0.1 % ference frequency	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference mode interference (peak value of interference < rated value of input range), min.	2 %  0.1 % ference frequency 40 dB	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/	2 %  0.1 % ference frequency 40 dB	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference with the suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression, min.  • Series mode interference (peak value of interference < rated value of input range), min.  • Common mode interference, min.	2 %  0.1 % ference frequency 40 dB  70 dB	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/	2 %  0.1 % ference frequency 40 dB  70 dB	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/	2 %  0.1 % ference frequency 40 dB  70 dB	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/	2 %  0.1 % ference frequency 40 dB  70 dB  Yes	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/	2 %  0.1 % ference frequency 40 dB  70 dB  Yes	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/	2 %  0.1 % ference frequency 40 dB  70 dB  Yes  Yes  No	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage voltag	2 %  0.1 % ference frequency 40 dB  70 dB  Yes  Yes  No  Yes  Yes	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage voltage voltage voltage voltage  • Common mode interference, min.  Interrupts/diagnostics/status information  Diagnostics function  Alarms  • Diagnostic alarm  • Limit value alarm  Diagnoses  • Monitoring the supply voltage  • Wire-break  • Short-circuit	2 %  0.1 % ference frequency 40 dB  70 dB  Yes  Yes  No	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage voltag	2 %  0.1 % ference frequency 40 dB  70 dB  Yes  Yes  Yes  Yes  Yes  Yes  Yes  Ye	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage voltag	2 %  0.1 % ference frequency 40 dB  70 dB  Yes  Yes  Yes  Yes  Yes  Yes  Yes  Ye	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage voltag	2 %  0.1 % ference frequency 40 dB  70 dB  Yes  Yes  Yes  No  Yes  Yes  Yes  Yes  Yes  Yes  Yes  Ye	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage value of interference value value of interference value value of interference value value value of interference value va	2 %  0.1 % ference frequency 40 dB  70 dB  Yes  Yes  Yes  Yes  Yes  Yes  Yes  Ye	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage value of interference voltage value of interference voltage value of interference voltage value of interference value of interference value value of interference value value of interference value value value of interference value value value of interference value value value value value of interference value va	2 %  0.1 %  ference frequency 40 dB  70 dB  Yes  Yes  Yes  Yes  Yes  Yes  Yes  Ye	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage voltag	2 %  0.1 %  ference frequency 40 dB  70 dB  Yes  Yes  Yes  Yes  Yes  Yes  Yes  Ye	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage voltag	2 %  0.1 %  ference frequency 40 dB  70 dB  Yes  Yes  Yes  Yes  Yes  Yes  Yes  Ye	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage voltag	2 %  0.1 %  ference frequency 40 dB  70 dB  Yes  Yes  Yes  Yes  Yes  Yes  Yes  Ye	
range), (+/-)  Operational error limit in overall temperature range  • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  • Current, relative to input range, (+/-)  Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage voltag	2 %  0.1 %  ference frequency 40 dB  70 dB  Yes  Yes  Yes  Yes  Yes  Yes  Yes  Ye	

<ul> <li>between the channels and backplane bus</li> </ul>	Yes	
<ul> <li>between the channels and the power supply of the electronics</li> </ul>	Yes	
Permissible potential difference		
between the inputs (UCM)	10 Vpp	
Isolation		
Isolation tested with	707 V DC (type test)	
Standards, approvals, certificates		
Ecological footprint		
<ul> <li>environmental product declaration</li> </ul>	Yes	
Global warming potential		
<ul><li>— global warming potential, (total) [CO2 eq]</li></ul>	88.3 kg	
<ul><li>— global warming potential, (during production) [CO2 eq]</li></ul>	13.1 kg	
<ul><li>— global warming potential, (during operation) [CO2 eq]</li></ul>	76.6 kg	
— global warming potential, (after end of life cycle) [CO2 eq]	-1.37 kg	
Highest safety class achievable in safety mode		
<ul> <li>Performance level according to ISO 13849-1</li> </ul>	PLe	
<ul> <li>Category according to ISO 13849-1</li> </ul>	Cat. 4	
SIL acc. to IEC 61508	SIL 3	
Probability of failure (for service life of 20 years and repair time	e of 100 hours)	
<ul> <li>Low demand mode: PFDavg in accordance with SIL3</li> </ul>	< 5.00E-05	
<ul> <li>High demand/continuous mode: PFH in accordance with SIL3</li> </ul>	< 1.00E-09 1/h	
Ambient conditions		
Ambient temperature during operation		
<ul> <li>horizontal installation, min.</li> </ul>	0 °C	
<ul> <li>horizontal installation, max.</li> </ul>	60 °C	
<ul> <li>vertical installation, min.</li> </ul>	0 °C	
• vertical installation, max.	50 °C	
Dimensions		
Width	15 mm	
Height	73 mm	
Depth	58 mm	
Weights		
Weight, approx.	48 g	

last modified: 10/9/2024 🖸